

PATENT APPLICATION

Method of Recording/Reproducing Digital Data and Apparatus for Same

Inventors: **Taku Hoshizawa**
Citizenship: Japan

Shigeki Taira
Citizenship: Japan

Osamu Kawamae
Citizenship: Japan

Assignee: **Hitachi, Ltd.**
6, Kanda Surugadai 4-chome
Chiyoda-ku
Tokyo, Japan
Incorporation: Japan

Entity: Large

- 1 -

METHOD OF RECORDING/REPRODUCING DIGITAL DATA AND
APPARATUS FOR SAME

BACKGROUND OF THE INVENTION

The present invention relates to an error correction technology to remove an error, in particular, to a digital data reproducing method, a
5 digital data recording method, and apparatus using error correction by product code. In particular, the present invention relates to a data recording and reproducing method, and an apparatus for performing interleave in byte unit to the data consisting of
10 multiple lines.

Although the present invention is widely applicable to digital data reproducing systems and recording systems that perform error correction by product code, it will be described here by citing a DVD
15 data reproducing system and a data recording system as examples.

A DVD (digital versatile disc) is a medium which is about 7 times larger than a CD (compact disc) in capacity. As a medium that records data on a DVD,
20 there are DVD-RAM, DVD-R, and DVD-RW. Recordable media are fields most expectable from now on, as seen in the recent growth of CD-R.

A format of DVD-RAM will be described below. In a present DVD, interleave is performed per row to
25 the data consisting of multiple lines.

First, an overview of demodulation processing of data recorded on DVD-RAM will be shown by using Fig. 3. The main data recorded is divided per 2048 bytes. In each, as shown in Fig. 4, 4 bytes of identification data (ID) 401, IED (ID Error Detection Code) 402 that is ID error detecting code parity, and 6 bytes of RSV (reservation bytes) 403 that is a reservation area are added. Furthermore, 4 bytes of error detecting code parity (EDC) is added to 2060 bytes of this data stream, then 2064 bytes of data unit (before scramble) 1 (304) is configured. Next, according to a scramble rule determined with the value of the ID part of the data unit 1, scramble processing is performed to 2048 bytes of main data part, and it becomes a data unit (after scramble) 1 (305) which is 12 rows \times 172 bytes. Furthermore, 16 bytes of Parity of Outer-code (PO) is added to each of 172 columns (lengthwise) of 192 rows \times 172 bytes that are configured by 16 data units 1 by making 16 blocks of these data units (after scramble) 1 (305) mutually combined. Next, 10 bytes of Parity of Inner-code (PI) is added to each of 208 rows (widthwise) containing PO to form one ECC block (307) which is a 182 rows \times 208 bytes cross Reed-Solomon code. Then, PO interleave which puts each of 16 rows of PO parts (including 16 rows of PI for them) into data units 1 as a 13th row is performed to form 16 data units 2 (308) (that is, one data unit 2 consists of 13 rows). After 8/16 modulation that converts all data

into 16 bits from 8 bits is given thereafter, 26 SYNC codes are added per one data unit 2 to form 16 data units 3 (309).

Hereafter, each data unit configuration will
5 be described in detail.

First, 2064 bytes of data is configured by,
as shown in Fig. 4, 2048 bytes of main data, 4 bytes of
identification data (ID401), IED (ID error Detection
Code) 402 that is ID error detecting code parity, 6
10 bytes of RSV (reservation bytes) 403 that is a
reservation area, and 4 bytes of EDC (error Detection
Code) 404. A data unit (after scramble) 1 (305) is a
data unit by making the 2064 bytes of data into the
form of 172 bytes \times 12 rows and scrambling 2048 bytes
15 of main data part.

16 data units (after scramble) 1 (306) is a
172 bytes \times 192 rows data field 306 configured by
combining 16 data units 1 (305) as shown in Fig. 5.

A 1ECC block 307 is a unit of error
20 correction processing in DVD and is product code (cross
Reed Solomon code). The product code will be formed as
follows. As shown in Fig. 6, outer-code configured by
defining 16 data units 1 as information data and making
each of 172 columns be RS (208, 192, 17) is formed (16
25 bytes of parity of outer-code P0502 is added as error
correction data). After that, inner-code is formed by
making 208 rows including P0502 be RS (182, 172, 11) in
the same direction as the direction of a main data list

and the recording direction in a DVD (parity of inner-code PI501 is added as error correction data).

A data unit 2 (308) is a data unit after the formation of the ECC block 307, and is a 182 bytes x 13 rows data unit that is configured by inserting each of 16 rows of PO502 into each data unit including PI501 (PO interleave) as shown in Fig. 7.

A data unit 3 (309) is a data train obtained by adding eight kinds (SY0-SY7) of synchronizing signals 801 (SYNC) at the head of each block every 91 bytes of the data unit 2 as shown in Fig. 8, for example, SY0 (SYNC code 0) in the head of the unit, SY1-SY4 cyclically inserted in the head of each row, and SY5, SY6 and SY7 inserted for identification of each row, and performing 8/16 modulation converting 8-bit data into 16-bit data. Moreover, it is possible to identify a position of data, which is reproduced, in the data unit 3 with the generating pattern of SYNC 801 from an addition method of this SYNC 801 at the time of reproduction.

After such conversion from the data unit 1 to the data unit 3, data modulated into a DVD is recorded with NRZI (Non Return to Zero) conversion being performed.

Moreover, the list of main data recorded on the DVD is never changed during data format conversion process such as scramble, ECC encoding, and PO interleave. Hence, the list and sequence of data

recorded on the DVD are equal to the list and sequence of main data.

Therefore, the data recorded on DVD is reproduced in a reverse process of data processing
5 performed in Fig. 3.

Hereafter, conventional data processing at the time of DVD reproduction will be described by using Fig. 9.

The 8/16 demodulation is performed while
10 determining a position in the data unit 3 (902) by using SYNC 801, and the data unit 2 (903) is generated. Next, PO interleave is released while determining a position of the data unit 2 in an ECC block by using ID 401, and an ECC block 901 corresponding to the ECC
15 block 307 before error correction is formed.

The reproduction data from the DVD has an error to occur by various factors. Hence, error correction to a maximum of 5 bytes per inner-code (normally, although each data constituting the code is
20 expressed by "word" or "symbol" in error correction, here, the data is explained by using "byte" as an example of a data unit) is performed in the error correction to inner-code having the same list as a data list recorded in the DVD. The correction of an error,
25 included in each outer-code, to a maximum of 16 bytes is performed, and error is removed by outer-code error correction. After that, error correction data PI 501 and PO 502 are removed from the ECC block 901, 16 data

units 1 (305) shown in Fig. 5 is obtained.

The data of the data unit 1 (305) releases the scramble (304) and is restored into ID, IED, RSV and 2048 bytes of main data (303) again after
5 performing the error detection processing by using EDC so as to verify that erroneous correction is not performed in the error correction processing.

The above is the overview of the data signal processing at the recording and reproduction of a DVD.

10 In the error correction processing in the reproduction of a DVD that is described by using Fig. 9, the error correction of a PI having an identical list with the one of the data recorded in the DVD is performed.

15 The relationship of data placement on DVD and data placement on ECC block is effective in view of making it possible to correct a comparatively long burst error by performing eraser correction, which uses a result as error position information in outer-code
20 error correction after not letting errors, continuously arising as shown by black parts in Fig. 10C, dispersed, and several uncorrectable error arising in the inner-code error correction. The vanishing correction is an error correction method of performing the correction by
25 determining outer-code error positions by using the correction result of the inner-code in this specification.

Nevertheless, an uncorrectable error arises

in plenty of outer-code when short burst errors randomly arising as shown by black parts in Fig. 10A pile on in a specific outer-code, error correction is impossible for the burst error in the inner-code error
5 correction, and the number of errors exceeds the number of correctable outer-code. (Figs. 10B and 10D will be described later.)

Moreover, in connection with the increase of high-density recording data for increasing capacity,
10 one or two bytes of error due to dust and scratches of a current DVD become a short burst error. Thus, a average length of error concerned (byte length) becomes long, and it is estimated that the case that an uncorrectable error arises will increase.

15 As a countermeasure for these errors, there is an invention disclosed in JP-A-8-125548.

This invention is a method of making an burst error dispersed in the entire product code by rearranging the predetermined data in the product code
20 every several bytes. Nevertheless, in the product code having a ratio of inner-code to outer-code like a DVD, there is a problem not to be able to secure correction capability, which is equivalent to a conventional method, for an burst error over ten or more lines.
25 This is because there is a case that, since the burst error is dispersed in the outer-code direction by performing the rearrangement between lines, an area of uncorrectable errors contrarily increases. On the

other hand, the present invention does not let an error dispersed in a outer-code because the present invention does not rearrange the data between lines, and hence it is possible to maintain correction capability for the
5 burst error.

Moreover, this is different from the present invention in that a rearrangement range is the entire ECC block and arrangement rules are not changed every line.

10 Other countermeasures for these errors are described in JP-A-3-266264 and JP-A-9-54956. These inventions are going to raise the tolerance for an burst error by arranging words, included in code words in the column and row directions, so that the words may
15 be mutually apart equally to or more than predetermined distance.

However, this invention is different from the present invention in that this invention does not change arrangement rules every line and performs
20 rearrangement over plural lines, and there is a possibility of not being able to maintain the burst error length.

SUMMARY OF THE INVENTION

An object of the present invention to provide
25 technology for raising correction capability of a short burst error, which is estimated to increase in future, while securing the correction capability, which is

equivalent to conventional technology, for an burst error over several tens of lines.

Major means of the present invention for solving an above subject will be described below.

5 The present invention is a data recording method of recording data on a record medium, and is intended to improve error correction capacity by rearranging data in sequence per byte for a data train consisting of two or more bytes which constitute the
10 error correcting code for recording data on this record medium and recording the data on the above-described record medium.

 In addition, the present invention is intended to improve the error correction capacity by
15 rearranging data per byte in sequence for parts of a data train except identification information out of the data train consisting of two or more bytes which constitute the error correcting code for recording data on this record medium, and recording the data on the
20 above-described record medium.

 Moreover, the present invention is intended to improve the error correction capacity by generating error correcting code through adding error correction data to the data for recording on this record medium,
25 rearranging data, forming this data train, per byte about the data train which constitutes this error correcting code, demodulating the data train which is rearranged in its sequence for data per byte, and

recording the modulated data train on the above-described record medium.

Further, the present invention is a data reproducing method that reproduces the data modulated and recorded on the record medium. The present invention is intended to improve the error correction capacity by demodulating the data train recorded on the record medium, restoring the data train, which is demodulated and rearranged according to the predetermined rule, to the data train in the sequence before being rearranged per byte for data forming the data train, correcting the errors that are included in the error correcting code restored to the data train in the sequence before being rearranged, and reproducing the data whose errors are corrected.

Furthermore, the present invention is a data recording apparatus recording data on a record medium. The present invention is intended to improve the error correction capacity by the data recording apparatus which comprises a circuit generating error correcting code for recording data on the record medium, a signal processing circuit which rearranges sequence for data per byte about a data train which consists of two or more bytes which constitutes the error correcting code, and a modulation circuit which modulates the data train which are rearranged in its sequence for data per byte.

Still further, the present invention is a data reproducing apparatus that reproduces data

modulated and recorded on a record medium. The present invention is intended to improve error correction capacity by a data reproducing apparatus characterized in comprising a demodulation circuit which demodulates
5 the data train recorded on the record medium, a signal processing circuit which restores the data which forms a the data train to the data train in the sequence before being rearranged in the sequence per byte about the data train that is demodulated by the demodulation
10 circuit and is rearranged according to a predetermined rule, an error correcting circuit which corrects the errors included in the error correcting code restored to the data train before being rearranged by the signal processing circuit, a reproducing circuit which
15 reproduces the data which had the error corrected by the error correcting circuit.

Thus, when the byte interleave for each row (here, the row talks noting that it has the same list as the data list recorded on the record medium) of a
20 product code is performed under a rule different every row, that is, when data rearrangement is performed according to the rule which is different every inner-code of the ECC block 307 in a DVD, several bytes to several tens bytes of short burst error is dispersed in
25 degree different every row. Hence, conventional errors shown in Fig. 10A become errors shown in Fig. 10B. Since an error count is equalized on outer-code in Fig. 10B even if uncorrectable errors are generated in the

outer-code error correction in Fig. 10A, the probability of further decreasing the errors included in data by the outer-code error correction becomes high.

5 This effect means that it becomes possible to obtain characteristics of error correction still better than those of a current DVD by performing the repetitive decoding, which performs the same error correction repeatedly again, after performing error
10 correction to inner-code and error correction to outer-code that are effective to random errors.

 Furthermore, if performing interleave processing within each row of the product code, it becomes possible to secure the burst correction length
15 the same as the former. This is because data dispersion does not occur in the direction of line of data formed by outer-code, even if the error generated like Fig. 10C is set to Fig. 10D by the byte
interleave.

20 Thus, in the present invention, an error count is equalized even at the time of an uncorrectable error arising conventionally, without changing burst correction length by performing the byte interleave every row of a product code under a rule different
25 every row, rearranging the data by using a rule different every row, and making the data dispersed so that several bytes to several tens bytes of short burst error may have not correlation. Hence, the probability

that more errors can be corrected becomes high.
Moreover, in many cases, in the repeat correction
having the excellent capacity to a random error, it
also becomes possible to correct errors more than those
5 in the past in a repeat count equal to or less than
that in the past.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a block diagram showing a data
processing flow at the time of recording when the
10 present invention is applied to a DVD;

Fig. 2 is a diagram showing an example of PI
interleave;

Fig. 3 is a block diagram showing a data
processing flow at the time of recording of the DVD;

15 Fig. 4 is a diagram showing a data unit 1
after scramble;

Fig. 5 is a diagram showing 16 data units 1
after scramble;

Fig. 6 is a diagram showing an ECC block;

20 Fig. 7 is a diagram showing 16 data unit 2;

Fig. 8 is a diagram showing a data unit 3;

Fig. 9 is a block diagram showing an example
of a data processing flow at the time of reproduction
of the DVD;

25 Figs. 10A-10D are drawings showing an effect
at the time of PI interleave for a short burst error
and a long burst error;

Fig. 11 is a diagram showing one ECC block after PI interleave;

Fig. 12 is a block diagram showing a data processing flow at the time of reproduction when the present invention is applied to the DVD;

Fig. 13 is a diagram showing an example of processing for canceling PI interleave;

Fig. 14 is a diagram showing an example of a data unit 2 after PI interleave;

Fig. 15 is a block diagram showing an example of a DVD recording and reproducing apparatus to which the present invention is applied;

Figs. 16A and 16B are block diagrams showing examples of M-series generating circuits;

Figs. 17A and 17B are block diagrams showing examples of M-series generating circuits;

Figs. 18A and 18B are block diagrams showing examples of constituting each address generating circuit by using an address decoder;

Fig. 19 is a block diagram showing an example of a PI interleave circuit;

Fig. 20 is a block diagram showing an example of a PI deinterleave circuit (circuit which cancels PI interleave);

Fig. 21 is a block diagram showing an example of PI interleave being performed for two inner-codes under one PI interleave conversion rule;

Fig. 22 is a block diagram showing an example

of PI interleave being performed every two bytes to one inner-code;

Figs. 23A and 23B are block diagrams showing examples of respective M-series generating circuits;

5 Fig. 24 is a block diagram showing an example of an arithmetic progression generating circuit;

Fig. 25 is a block diagram showing an example of a PI interleave circuit; and

Fig. 26 is a block diagram showing an example
10 of a PI deinterleave circuit (circuit which cancels PI interleave).

DESCRIPTION OF THE EMBODIMENTS

Hereafter, the present invention will be described by using drawings. Here, the present
15 invention will be described by making a DVD data reproducing system, and a data recording system be examples.

Fig. 1 shows an example of showing data processing steps at the time of recording when the
20 present invention is applied to a current DVD logical format shown in Fig. 3.

Fig. 1 will be briefly described. The main data recorded is divided per 2048 bytes. In each head, as shown in Fig. 4, 4 bytes of identification data (ID)
25 401, IED(ID error Detection Code) 402 that is ID error detecting code parity, and 6 bytes of RSV(reservation bytes) 403 that is a reservation area are added.

Furthermore, 4 bytes of error detection code parity (EDC) is added to 2060 bytes of this data stream, then 2064 bytes of data unit (before scramble) 1 (304) is configured. Next, according to a scramble rule

5 determined with the value of the ID part of the data unit 1, scramble processing is performed to 2048 bytes of main data part, and it becomes a data unit (after scramble) 1 (305) which is 12 rows \times 172 bytes.

Furthermore, 16 bytes of Parity of Outer-code (PO) is

10 added to each of 172 columns (lengthwise) of 192 rows \times 172 bytes that are configured by 16 data units 1 (306) by making 16 blocks of these data units (after scramble) 1 (305) mutually combined. Next, 10 bytes of Parity of Inner-code (PI) is added to each of 208 rows

15 (widthwise) containing PO to form one ECC block (307) which is a 182 rows \times 208 bytes cross Reed-Solomon code. Next, the data in each row of the ECC block is rearranged every one byte according to each rule to obtain an ECC block 101. Then, PO interleave which

20 puts each of 16 rows of PO parts (including 16 rows of PI for them) into data units 1 as a 13th row is performed to form 16 data units 2 (102) (that is, one data unit 2 consists of 13 rows). Then, after 8/16 modulation that converts all data into 16 bits from 8

25 bits is given, 26 SYNC codes are added per one data unit 2 to form 16 data units 3 (103).

However, although PI interleave is performed immediately after ECC block generation in Fig. 1,

naturally, it is no problem to perform PI interleave after constituting the data unit 2, or after constituting the data unit 3.

Moreover, the "word" and the "symbol" which
5 are the unit of data are also described as a "byte" here.

In Fig. 1, the added PI interleave means byte interleave processing for rearranging the sequence on the basis of a certain rule for 182 bytes of data
10 (inner-code) of each row in the ECC block of DVD as shown in Fig. 2. That is, the added PI interleave shows the processing for rearranging the byte sequence about the data train which consists of a plurality of bytes constituting error correcting code. Here, the
15 data train means an inner-code forming the ECC block, that is, an arrangement of the data in the row direction. At this time, the effect in the point of dispersion of errors becomes large by using conversion rules (interleave rules) $F_i(x)$ ($=y$) that have no
20 correlation and different from one another in 208 rows of inner-code included in the ECC block. However, it is possible to obtain the effect of error dispersion even if this PI interleave is performed by using at least two kinds of conversion rules (interleave rules)
25 $F_1(x)$ and $F_2(x)$. Moreover, data $D_{i, 0}; D_{i, 1}; D_{i, 2}; \dots; D_{i, 181}$ show the data constituting the inner-code in the i -th row of an ECC block, and $D_{i, 171}; D_{i, 172}; \dots; D_{i, 181}$ correspond to the parity of inner-

code PI. Therefore, the data train (B) generated by performing PI interleave to the data train (A) is not always inner-code.

It is also possible to perform PI interleave, which rearranges the record sequence of this data, among a plurality of inner-codes. In this case, although it becomes possible to obtain still higher correction capacity to a random error, burst error length become short.

Fig. 11 is a diagram showing an ECC block (101) after PI interleave shown in Fig. 1. This shows the status that each row of the ECC block shown in Fig. 6 is given PI interleave and is transformed.

Fig. 12 shows a data conversion flow at the time of recording data, generated after data conversion shown in Fig. 1, on a DVD and reproducing the data.

In Fig. 12, a data unit 2 (1203) is generated from the data recorded on the DVD while determining the position in the data unit 3 by using SYNC801, and performing 8/16 demodulation. Next, an ECC block (1201) which is given PO interleave processing and is shown in Fig. 11 is formed by canceling PO interleave while determining the position of the data unit 2 in the ECC block 307 by using ID401. Then, the ECC block (1201) is restored to an ECC block (901) shown in Fig. 6 by applying the conversion rule $G_i(y)$, which is the inverse transformation of $F_i(x)$ and is shown in Fig. 13, that is, performing every row PI deinterleave which

performs conversion of restoring again the symbol train (A), obtained by data rearrangement at the time of modulation, to PI code (B). After this, as usual, an error of up to 5 bytes is corrected in each inner-code by the error correction to inner-code, and an error of up to 16 bytes, included in each outer-code, by the error correction to outer-code is corrected (306). Then, ID, IED, RSV, and 2048 bytes of main data (303) are obtained again after removing the data PI and PO for error correction required for error correction processing, restoring the ECC block to the 16 data unit 1 (305) shown in Fig. 5, canceling scramble (304), and performing error detection processing by using EDC. In addition, as for conversion rules $F_i(x)$ and $G_i(x)$, the apparatus may have the information as rules defined beforehand. Alternatively, the conversion rules $F_i(x)$ and $G_i(x)$ may be recorded every medium, and the apparatus may read the information. In the case of the latter, it is possible to perform the above-described processing after reading conversion rules $F_i(x)$ and $G_i(x)$ first, and to determine the conversion rules $F_i(x)$ and $G_i(x)$ for every disk unit, ECC block unit, frame unit, or the like in the apparatus.

However, as shown in Fig. 12, in case demodulation processing is usually performed in DVD used as an example in this explanation, the position in the ECC block is determined by using ID. Hence, when PI interleave which is different in every row of all

ECCs is applied, if PI interleave processing at the time of record is applied, it is not possible to determine $x=G_i(y)$ used in PI deinterleave at the time of restoring a data train since a conversion rule $y=F_i(x)$ for PI interleave for a row including ID cannot be found. Hence, it becomes very difficult to seek the ID.

Therefore, the information showing the position in a product code is shown, that is, ID and IED (IED is also required when the reliability of ID is required) are removed from the objects of data interleave on a DVD, and rows including this information are given PI interleave processing only to 176 bytes of data except identification information such as ID and IED.

When this is applied to a DVD, the data unit 2 (102) shown in Fig. 1 becomes as shown in Fig. 14. In this case, identification information containing EDC, RSV, etc. cannot be obtained until the code is decoded into the original inner-code by performing PI deinterleave since all the data except ID and IED are set as the objects of scramble.

Therefore, although the effect of PI interleave becomes a little weak when the information which is needed before forming an ECC block in RSV etc. at the time of reproduction is included, it is necessary to remove the data as well as ID from the objects of the interleave.

Moreover, as shown in Fig. 14, if removing ID and IED from the objects of PI interleave, in regard to the conversion rules $F_i(x)$ of the inner-code including ID and IED, it is assumed that $x=1, \dots, 182$ and the values of x show position addresses as shown in Fig. 2. Then it should be devised to become $F_i(n) = n$ ($n=1, 2, 3, 4, 5$, and 6), or it is made to limit x and $F_i(x)$ in a range of 6 to 182.

Fig. 2 on which is briefly touched above will be described again. Fig. 2 is an example of a diagram having shown the method of a data list at the time of adopting PI interleave with the conversion rule $F_i(x)$ for PI interleave to the inner-code described in Fig. 6 where the present invention is described above. An inner-code is 182 bytes of data train, data (A) denotes the inner-code after the addition of PI and PO, and data (B) denotes 182 bytes of data train which is given PI interleave by the conversion rule $F_i(x)$ and is rearranged in the sequence of data thereof. Here, although the data (B) is an example of rearranging data every 13 pieces, the conversion rule $F_i(x)$ is not limited to this, but is enough to discontinuously rearrange the data.

Two or more kinds of conversion rules $F_i(x)$ are prepared in order to perform different values of PI interleave. In a DVD, the conversion rules of up to 208 kinds are prepared, and error counts on outer-codes in an ECC block are equalized as shown in Figs. 10A to

10D by applying the different conversion rule for every
inner-code. Hence, cases that error correction to
outer-codes become possible increases. Thus, it
becomes possible to increase correction capacity by
5 performing different PI interleave to the inner-codes
and recording the inner-codes on a record medium.
Moreover, this effect becomes still larger when the
code is decoded repeatedly.

Next, a method of implementing the conversion
10 rule for this PI interleave in a circuit will be
described. First, an example of configuration of a DVD
recording and reproducing apparatus at the time of
applying the present invention will be described by
using Fig. 15. Although a recording and reproducing
15 apparatus is described as an example here, a present
invention is applicable also to a reproduction
dedicated device and a record dedicated device.

A pickup 1502 performs record and
reproduction of data on a record medium 1501 such as a
20 DVD, and a spindle motor 1503 rotates a disk.
Moreover, a servo 1504 controls the optical pickup 1502
or the like. A read channel 1505 performs waveform
equalization and doubling of an analog reproductive
signal read from the record medium 1501, and
25 synchronous clock generation. A decoder 1506 consists
of a demodulation circuit 1507 performing 8/16
demodulation of data read, and an error correcting
circuit (1508, 1518) performing the processing of

removing errors included in the data, and RAM 1509a temporarily stores the data at the time of reproduction. RAM 1509b temporarily stores the data at the time of record. This can be also used as the RAM
5 1509a. Numeral 1514 is a laser driver. A modulation circuit 1512 performs the modulation of the data at the time of record, and an encoding circuit 1513 consists of an error correcting code generation circuit adding parity of error correcting code, PI and PO, and a
10 scramble circuit performing scramble processing. An interface 1515 controls the input/output of data with a host system, and a microcomputer 1516 generalizes the system. In addition, it is also possible to use a microcomputer as the error correcting code generation
15 circuit adding the error correcting code parity PI and PO.

A PI interleave circuit (signal processing circuit which rearranges the data in an inner-code as shown in Fig. 2) 1517 implements the present invention,
20 and a PI deinterleave circuit 1518 is a signal processing circuit which performs cancellation of PI interleave and processing shown in Fig. 13. That is, the PI interleave circuit 1517 rearranges the sequence of word bytes for the data train which consists of a
25 plurality of word bytes who constitutes an error correcting code, and the PI deinterleave circuit 1518 restores the data train, which is rearranged, to the data train in the sequence before being rearranged.

The PI interleave circuit 1517 has SRAM and a register which can store at least 182-byte data in a system where PI interleave closed within one inner-code is performed. Hence, the PI interleave circuit 1517
5 reads data every inner-code from the RAM 1509b after ECC block generation at the time of record, and temporarily stores the data in the sequence at the time of being read, that is, in the form of an inner-code in the register. After that, the PI interleave circuit
10 1517 writes the data on the register again in RAM 1509b while converting the data list according to predetermined PI interleave conversion rules.

The PI deinterleave circuit 1518 has SRAM and a register which can store at least 182-byte data in a
15 system where PI interleave closed within one inner-code is performed. At the time of the reproduction after data is read from a DVD, the PI deinterleave circuit 1518 reads data from the RAM 1509a every inner-code immediately after 8/16 demodulation and temporarily
20 stores the data in the register in the present sequence. After that, the PI deinterleave circuit 1518 writes the data on the register again in RAM 1509a while converting the data list according to predetermined PI interleave conversion rules.

25 Moreover, similar processing can be also performed in the following configuration. That is, in the PI deinterleave circuit 1518, the numbers of SRAM and registers are increased, and arranged just after the

demodulation circuit in the decoding circuit 1508, and the data outputted from the demodulating circuit is directly inputted into the register so that the data train having the byte count equivalent to the count of the inner-code is arranged. Then, the PI deinterleave circuit 1518 arranges the data, saved in the register, in the RAM 1509a while performing PI deinterleave of the data.

Next, a PI interleave circuit and a PI deinterleave circuit that are shown in Fig. 15 will be described. Fig. 19 shows an example of the PI interleave circuit 1517 where PI interleave conversion rules are defined by using the M-series generating circuit 1901 (a circuit generating the maximum periodic column, and the maximum period column (= M-series) is 255 at the time of using an 8-bit register. Moreover, here, it is assumed that the inner-code read from the RAM 1509b has been already stored in a shift register 1902. As write control signals to the RAM 1509b, there are a write request signal, an address (however, referred to as 1 to 182 for convenience here) in the RAM 1509b, and write data. When the write request signal is outputted, a write request acknowledge signal, which shows that data is written, is inputted from the RAM 1509b.

In this circuit, when the write request acknowledge signal is inputted, that is, the timing when the data is written, the shift register 1902

shifts. Moreover, the M-series generating circuit 1901 also changes to the following value if the write request acknowledge signal is inputted, or if the signal of 1 to 255 generated by the M-series generating circuit 1901 exceeds the address to be required, i.e., if the signal has the value of 183 or more. Here, the value range is not necessary to be 1 to 255. In a DVD, the inner-code is 182 bytes, and PI interleave in the data in all the inner-codes is concerned here. Hence, an output from the 8-bit M-series generating circuit is used. Moreover, the write request signal is outputted when the address made in the M-series generating circuit 1901 is judged to be 182 or less by a request generation judging circuit 1903.

15 This is to make an address skipped if the address made in the M-series generating circuit 1901 exceeds 183, because PI interleave processing cannot be performed.

Fig. 20 shows an example of the PI deinterleave circuit 1518 where PI interleave conversion rules are defined by using the M-series generating circuit 1901. Moreover, here, it is assumed that the data train read from the RAM 1509a has been already stored in a register 2001.

25 As write control signals to the RAM 1509a, there are a write request signal, an address in the RAM 1509a, and write data. When the write request signal is outputted, a write request acknowledge signal, which

shows that data is written, is inputted from the RAM 1509a.

In this circuit, when the value of the same M-series generating circuit 1901 as the M-series
5 generating circuit 1901 where the PI interleave conversion rules are defined exceeds 183, the following value is outputted from the M-series generating circuit 1901. When the value is 182 or less, a write request is generated, and one byte of data in the data train
10 chosen with the value of this M-series generating circuit 1901 is written in the address which a counter 2002 shows. Moreover, since a write request acknowledge signal is inputted when writing is performed, the counter 2002 which generates an address
15 shows the following value, and the M-series generating circuit 1901 also shows the following value.

In this circuit also, it is necessary to make an address skipped if the address made in the M-series generating circuit 1901 exceeds 183, because PI
20 deinterleave processing cannot be performed.

Moreover, in these circuits, if an address is 1 to 6 in the request generation judging circuit in the inner-code containing ID, the address is treated similarly to a case of being 183 or more. When
25 overwriting the data train, which is given PI interleave, to the original inner-code of the RAM 1509b, i.e., the inner-code stored in the register 1902, it is not necessary to write ID and IED in the

RAM 1509b. Moreover, when storing the data train in another area of the RAM 1509b, a system writing ID and IED in a predetermined position is added.

However, a countermeasure for the inner-code containing ID can be easily achieved by adding an offset to an address, or the like.

Many kinds (208 or more kinds required of PI interleave conversion rules which are different in all inner-codes in a DVD) of M-series defining PI interleave rules that are used in Figs. 19 and 20 can be generated in the following combination.

This can be easily implemented by combining the following items 1 and 2.

1. Changing of the kind of feedback of the shift register generating M-series (corresponding to the relation between Figs. 16A and 16B).
2. Rearrangement of the position of data outputted from the shift register (corresponding to the relation between Figs. 16A and 17A).

For example, it is assumed that the positions of the data outputted from the shift register in 13 inner-codes in the data unit 2 are rearranged by changing the feedback rules of the M-series generating circuit every unit of the data unit 2 in Fig. 1, i.e., every unit of the data unit in Fig. 14. Then, it is possible to obtain 208 kinds of different PI interleave conversion rules.

Moreover, different M-series can be also

generated by changing the polarity of a certain bit as shown in Fig. 17B. However, since zero may be outputted from M-series in this case, and a value at the time of the register being zero and an address is not generated at the value "AA=170" in hexadecimal notation in Fig. 17B, it becomes necessary to perform such a device that an address is calculated by subtracting 170 from the obtained value. However, these can be used as M-series that define PI interleave rules. Moreover, similarly, it is clear that an address can be converted by using a logic circuit obtained by combining OR, AND, and NOT.

As shown in Fig. 23A, values obtained by adding values different in every row (however the same row fixed value) to the value outputted from each M-series generating circuit 1901 in Figs. 16A, 16B, 17A, and 17B that are shown above are also M-series. Hence, the M-series can be used as PI interleave conversion rules according to the present invention. However, in this case, a carry to the ninth bit (MSB) that is generated by performing addition is ignored.

Moreover, values obtained by substituting a multiplier 2303, as shown in Fig. 23B, for an adder 2302 in this diagram, and multiplying the fixed value corresponding to each row on a finite field $GF(2^8)$ are also M-series. Hence, the M-series can be used as PI interleave conversion rules according to the present invention. A line-counter 2301 counts the position of

the inner-code in a product code, i.e., a line address.

As a method of generating a plurality of PI interleave conversion rules that is for achieving the object of the present invention to performs PI
5 interleave, that is, for making burst errors, produced at random per several bytes, equally dispersed in all outer-codes, and is a simplest circuit, there is a method of changing the initial value of the M-series generating circuit 1901 shown in Fig. 19 according to a
10 row. This means that M-series generated by the same M-series generating circuits 1901 are generated by shifting the M-series. As an example, there is a method of substituting a row address as the initial value of each PI interleave conversion rule. Thereby,
15 at least 182 kinds of PI interleave conversion rules are generated. However, in order to use PI interleave conversion rules which are different in all 208 rows, it is necessary to combine this method with another PI interleave conversion rule generating method. In
20 addition, as long as a method can change M-series according to a row, the method besides the above-described examples can be used.

It is also possible to realize the PI interleave circuit 1517 and PI deinterleave circuit
25 1518, which are shown in Fig. 15, with another method without using the M-series generating circuit 1901.

This is a method of realizing PI interleave conversion rules with ROM or a circuit as shown in

Figs. 18A and 18B instead of the M-series generating circuit 1901. In particular, this is effective when only several kinds of PI interleave conversion rules are necessary. Moreover, a still higher effect is
5 expectable in that an address can be set freely such that PI interleave rules are managed with the distance between data adjacent to each other in an inner-code in order to advance random characteristics.

Moreover, there is a method of using
10 arithmetic progression as a method except methods using M-series as PI interleave conversion rules.

Here, since what is necessary is just to use 182 arbitrary numbers as PI interleave rules in a DVD as PI interleave rules, suppose that numbers 0 to 181
15 are used.

This is a method of rearranging the list of an inner-code according to arithmetic progression, for example, rearranging positions of the data in the inner-code according to PI interleave rules, that is,
20 0, 3, 6, 9, ..., 177, 180, 1, 4, 7, ..., 178, 181, 2, 5, 8, ..., 176, 179 in the case of using a progression where numbers increases by 3.

In this case, it is necessary to use a constant, which is different in each row, as an
25 increment. Nevertheless, when numbers that are coprime to 182 are used as constants, in regard to numbers exceeding 181, values obtained by subtracting 182 from the numbers can be used as the constants. However,

when numbers that are not coprime to 182 are used as constants, for example, when the increment is 2, the numbers become 0, 2, 4, 8, ..., 180, 0, 2, 4, ..., and hence it becomes necessary to provide a system of
5 adding one when exceeding 182 so that the same numbers may not appear twice.

Moreover, if most target burst errors generated at random are 10 bytes or less, it is better to choose 11 or more as an incremental constant.

10 However, when 182 bytes are selected as an inner-code when an arithmetic progression is used, it is necessary to note that the case where one is selected as a constant and the case that 181 is selected as a constant are the same in an object of
15 dispersing errors in the different outer-codes.

This is because adjacent numbers become the same although there is difference between the left and the right since the list becomes 0, 1, 2, 3, 4, ..., 181 when one is selected as a constant, and the list
20 becomes 0, 181, 180, ..., 4, 3, 2, 1 when 181 is selected.

An example (only numbers that are coprime to 182 except one are used) of the circuit that generates an arithmetic progression is shown in Fig. 24.

25 In this diagram, an incremental constant is selected and used by being switched according to the value of a row address changed and is used so that values outputted from an 8-bit register 2401 becomes an

arithmetic progression and a different series as much as possible may be obtained according to an inner-code, that is, according to a row.

Moreover, Figs. 25 and 26 show examples where
5 arithmetic progressions are applied to the PI
interleave circuit 1517 and PI deinterleave circuit
1518 in Fig. 15. This can be configured only by
replacing the M-series generating circuit 1901 in Figs.
19 and 20, which is described above, with the
10 arithmetic progression generating circuit 2501 in Fig.
24.

The circuit in Fig. 19 is cited as an example
of the M-series generating circuit 1901 of the PI
interleave circuit 1517 in Fig. 15, and the method of
15 arranging data in the addresses which corresponds to an
M-series every one byte from a head of the data in an
inner-code is shown. However, there is a method of
arranging the data, stored at the positions on the
inner-code generated by the M-series, in order of the
20 M-series by using the PI deinterleave circuit 1518 in
Fig. 20 as the PI interleave circuit 1517.

Moreover, Fig. 19 shows the PI deinterleave
circuit 1518 corresponding to this.

Naturally, when a different M-series is used
25 and this method is also used, the object to disperse
burst errors on different outer-codes can be attained.

However, when this method is used, burst
errors cannot be dispersed on different outer-codes by

changing the initial value of an M-series in each row.

The relation between two kinds of these PI interleave methods are the same as the arithmetic progression generating circuits 2501 described by using
5 Fig. 25 showing the PI interleave circuit 1517 and Fig. 26 showing the PI deinterleave circuit 1518.

PI interleave conversion rules can be configured by some combinations containing the M-series and arithmetic progression, which are introduced above,
10 as well as one method, and the circuit which realizes them can be also realized by the combination of respective elements.

Moreover, it is also good to combine address decoders 1801 and 1802 constituted by the M-series
15 generating circuit 1901, ROM, and circuits in order to generate many PI interleave conversion rules.

Moreover, in order to take PI interleave conversion rules into consideration from a circuit and to perform transform processing at high speed, as shown
20 in Fig. 21, it is possible to simultaneously perform a plurality of PI interleave by using the same conversion rule. It is also possible to simultaneously perform two or more bytes (2 bytes in Fig. 22) of PI interleave within the same inner-code, as shown in Fig. 22. That
25 is, it is possible to make two or more bytes be a group, and to rearrange the order of groups by a group.

When these are actually implemented into circuits, the optimal PI interleave method can be

selected in consideration of the bus width of RAM, and data allocation according to processing speed required. In addition, it is necessary to also take into consideration of the circuit scale at the time of
5 implementation, and the degree of performance improvement obtained by the present invention.

Moreover, although these diagrams show examples at the time of performing PI interleave by 2 bytes unit, three or more are sufficient as the size of
10 the inner-code to which the same PI interleave is actually applied.

Although cases where the present invention is applied to a DVD are described through embodiments, the present invention is effective at a digital data
15 recording and reproducing apparatus, including a product code, and a digital data recording and reproducing method.

In addition, it should be noted that, when record to a record media is performed according to the
20 list of the outer-code in a product code, the inner-code used in explanation corresponds to the outer-code. Moreover, although the signal processing circuit using an M-series and an arithmetic progression is exemplified in the PI interleave circuit 1517 and PI
25 deinterleave circuit 1518, other pseudo-random number generating circuits or the like can be used.